



Product data sheet

49913G/L1 - Junction box FK Technofil 3P C1 outer conductor L1



Junction box 3P outer conductor L1 with socket 3-pole code 1

Characteristics	
Eldas number	150748037
Base Unit	Piece
availability	Delivery in 3 weeks
EAN Code	7611718218231
group	170000
Packing	50
country of origin	CH
Customs tariff number	8536.9080
Weight (g)	69,15 g
Color	gray
Coding plug connection	Code 1
Technical data	
Box Type	Junction boxes
Fire load (KWh)	0,42 kWh
Dimensions length x width x height (mm)	88x38x38 mm



Product data sheet

49913G/L1 - Junction box FK Technofil 3P C1 outer conductor L1

Dimensions length x width x height (inch)	3,46x1,5x1,5 inch
Degree of protection	IP20
Metal parts	Korrosionsgeschützt
Flat cable contacting type	Piercing-Kontaktierung (Schraube)
Number of poles	3 pole
Rated current heavy current part (A)	16 A
Rated voltage heavy current part (V)	250 V
Operating Temperature (°C)	-15 bis 85 °C
Installation temperature min. (°C)	5 °C
Plastic parts	Halogenfrei
Material slider/bottom part	Polyamid, schwarz
Material housing	Polyamid, grau
Material hood	Polycarbonat, transparent
Number Screwdriver Pointed screws Heavy current part	1
Operating torque of pointed screws for heavy current section (Nm)	0,7 Nm



Product data sheet

49913G/L1 - Junction box FK Technofil 3P C1 outer conductor L1

Product accessories

	Stecker_01_03 - Connexions enfichable Code 1 pour tension de réseau, 3 pôles null
--	---



Product data sheet

49913G/L1 - Junction box FK Technofil 3P C1 outer conductor L1

Product systems



Flat cable system Technofil 5G2.5mm²



Due to the versatile range of junction boxes, this system meets numerous, complex requirements for consumer lines.

You can combine the connections in such a way that they alternately feed single-pole or multi-pole consumers, that consumers are assigned to different switching groups (energy-saving circuits), that alternating single-pole consumers are distributed to three pole conductors (load balancing), that selected consumers such as emergency lights, cash registers, etc. are assigned to safety or emergency power supplies, or that fixed or plug-in connections are used as required to facilitate service work.
